

Počiatočný stav

- [Oneplus One](#) s custom ROM
- Stiahnutý firmware [Stock CM11s verzia 38R](#)
- funkčné prepojenie PC - [Oneplus One](#) (fastboot mód - [Návod body 1 až 3](#))
- bootloader musí byť odomknutý - [Návod na odomknutie bootloderu](#)

Postup

- **Následovný postup urobí kompletný WIPE telefónu - vymazanie všetkých údajov!!!**
- **Preto si potrebné veci odzálohujte!!!**

1. Stiahnutý [cm-11.0-XNPH38R-bacon-signed-fastboot_64GB.zip](#) rozbalíme do adresára s fastboot.exe
2. [Oneplus One](#) prepojíme s PC a prejdeme do fastboot módu
3. V termináli/cmd na počítači spustíme flash-all.bat (je medzi rozbalenými súbormi) - pre info výpis dávkou:@ECHO OFF
:: Copyright 2012 The Android Open Source Project
::
:: Licensed under the Apache License, Version 2.0 (the "License");
:: you may not use this file except in compliance with the License.
:: You may obtain a copy of the License at
::
:: <http://www.apache.org/licenses/LICENSE-2.0>
::
:: Unless required by applicable law or agreed to in writing, software
:: distributed under the License is distributed on an "AS IS" BASIS,
:: WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied.
:: See the License for the specific language governing permissions and
:: limitations under the License.

```
PATH=%PATH%;"%SYSTEMROOT%\System32"
```

```
fastboot flash modem NON-HLOS.bin
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash sbl1 sbl1.mbn
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash dbi sdi.mbn
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash about emmc_appsboot.mbn
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash rpm rpm.mbn
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash tz tz.mbn
```

```
fastboot reboot-bootloader
```

```
ping -n 5 127.0.0.1 >nul
```

```
fastboot flash LOGO logo.bin
```

```
fastboot reboot-bootloader
ping -n 5 127.0.0.1 >nul
fastboot -w update cm-11.0-XNPH38R-bacon-signed-fastboot.zip
```

```
echo Press any key to exit...
pause >nul
exit
```

4. Hotovo

Poznámka:


Dávka **flash-all.bat** funguje aj s originálnym firmware 38R zverejnený na stránke CyanogenMódu (stačí si ho vyrobiť, kompletný výpis tejto dávky je uvedený vyššie).
 Stačí stiahnuť [Originálny CM11s 38R](#) a rozbaľiť do adresára s fastboot.exe vrátane stiahnutého zip archívu - pozri výpis všetkých súborov (nemal by žiadny chýbať, ani zip!).

```
06. 10. 2014 11:14          14 android-info.txt
01. 01. 2009 00:00    5`711`872 boot.img
06. 10. 2014 12:43    10`682`660 cache.img
29. 10. 2014 08:43   510`413`031 cm-11.0-XNPH38R-bacon-signed-
fastboot.zip
06. 10. 2014 11:14    385`400 emmc_appsboot.mbn
06. 10. 2014 11:14     665 filesmap
06. 10. 2014 12:43     210 flash-radio.sh
06. 10. 2014 11:14    9`821`696 logo.bin
06. 10. 2014 12:43     730 md5sum-fastboot.md5
06. 10. 2014 11:14   57`689`600 NON-HLOS.bin
01. 01. 2009 00:00    7`690`240 recovery.img
06. 10. 2014 11:14    190`168 rpm.mbn
06. 10. 2014 11:14    302`704 sbl1.mbn
06. 10. 2014 11:14     11`800 sdi.mbn
01. 01. 2009 00:00   820`516`276 system.img
06. 10. 2014 11:14    290`232 tz.mbn
06. 10. 2014 12:43   140`462`880 userdata.img
06. 10. 2014 12:43   144`460`844 userdata_64G.img
```

[zdroj - XDA](#)

fastboot flash oppostanvbk-static_nvbk.bin --doplniť

[Návrat](#)



From:

<http://oneplus.jecool.net/> - **Oneplus One**

Permanent link:

<http://oneplus.jecool.net/doku.php?id=start:guides:rts>

Last update: **2014/12/02 09:06**

